



Bluetooth 5.1

SMARTCOM

di **MIDLAND**



2 - POCKET GUIDE

DESCRIPTION - LEGENDA



	AUDIO FEEDBACK	
Button + / Button -	Sound alert	Red/blue led blinking
Press X sec.	VISUAL FEEDBACK	Purple led
Press X times	Blue led blinking	Steady blue led
	Red led blinking	Steady red led







POWER ON

	Press 3 sec.
	Led Blinking
	"Power on"
	Battery status









POWER OFF

	Press 3 sec.
	Led Blinking
	"Power off"

PAIRING TO PHONE/GPS

Status: Power off	
	Press 7 sec.
	Led blinks alternately
	Searching Bluetooth device on your phone. If needed, enter PIN code (0000).
	Four led blinkings
	"Pairing successful"
	"Device connected"






PAIRING ANOTHER SMARTCOM OR MIDLAND

Status: Both units powered on	
   	Press 7 sec. on both devices
	"Pairing"
	Led blinks alternately on both devices
	Three led blinkings on both devices
	"Pairing successful"




PAIRING TO A DIFFERENT MODEL/BRAND UNIT

Status: Both units powered on	
Press 7 sec.	
Led blinks alternately	Follow the "phone" pairing procedure
	"Pairing"
Both units stop flashing	
	"Pairing successful"








OPEN/CLOSE INTERCOM

Status: units on and paired	
  	Press once
	"Beep"
	Led blinks: audio active













RESET ALL PAIRINGS

Status: power on	
	Press 9 sec.
	Steady led for 3 sec.
	"Beep"

VOICE CALL





Status: unit on and connected to a phone	
  	Press twice
	Voice assistant (Google assistant, Siri)
  	Press twice to end the call

ANSWER A CALL






Status: phone rings	
	   <p>Press once to answer a call</p>
	   <p>Press once to end a call</p>
	   <p>Press 3 sec. to reject a call</p>

To turn off/on the Auto Answer when device is turned off, press + and - for 9 seconds.





VOLUME ADJUSTMENT

Status: while listening to an audio source (intercom, music, phone call...)	
	 Keep pressed to increase the volume
	 Keep pressed to decrease the volume


MUSIC

Status: unit on and connected to the phone	
	Select a music APP from the phone
	Press 1 time Play/Pause
	Blinking
	Press 3 times Song forward
	Press 3 times Song backward

CHANGE LANGUAGE

Status: unit on	
	 Keep pressed for more than 9 seconds 
	"Battery status" in the various languages. Release + button to select the desired one.

Frequency	2.4GHz
Max power	100mW



The power supplied by the charger must be between min 05 watt required by the radio equipment, and max 05 watt to achieve maximum charging speed.

To download the complete manual visit www.omniaretail.it



Distributed by:
OMNIA RETAIL srl
Via T. Grossi, 5 - 20841 Carate Brianza
MB (Italia) - www.omniaretail.it

Produced and imported by:
MIDLAND EUROPE srl
Via R. Sevardi 7 - 42124 Reggio Emilia
Italia